

Name of supplier	KW-Commerce GmbH
Address of supplier	Jägerstr. 41 10117 Berlin Deutschland
Model Identifier	46680.7.06
Model registered as	955848



Katharina Zelisko, Business Unit Director

28 October 2021

Technical Data

General Data

useful luminous flux (Φ_{use}) in lm	525
colour rendering index (CRI)	80
on-mode power (P_{on}) in W	7.6
beam angle in degrees for directional light sources (DLS)	38
correlated colour temperature (CCT) in K	2900
standby power (P_{sb}) in W	NA
networked standby power (P_{net}) in W for connected light sources (CLS)	NA
displacement factor ($\cos \phi_1$) for LED and OLED mains light sources	0.8
colour consistency in MacAdam ellipse steps for LED and OLED light sources	6
luminance-HLLS in cd/mm ² (only for HLLS)	NA
flicker metric (P_{stLM}) for LED and OLED mains light sources	1
stroboscopic effect metric (SVM) for LED and OLED mains light sources	0.4

Excitation purity, only for CTLS, for the following colours and dominant wavelength within the given range

Blue 440 nm — 490 nm
Green 520 nm — 570 nm
Red 610 nm — 670 nm

Calculations

Energy Efficiency Class

$\eta_{TMC} = (\Phi_{use}/P_{on}) \times F_{TM}$ (lm/W)	On-mode power (P_{on}), expressed in W	7.6
<i>Table 1</i> Energy efficiency classes of light sources		
Useful luminous flux (Φ_{use})		525
F_{TM}		1.176
η_{TM}		81
Energy efficiency class	Total mains efficacy η_{TMC} (lm/W)	
A	$210 \leq \eta_{TMC}$	
B	$185 \leq \eta_{TMC} < 210$	
C	$160 \leq \eta_{TMC} < 185$	
D	$135 \leq \eta_{TMC} < 160$	
E	$110 \leq \eta_{TMC} < 135$	
F	$85 \leq \eta_{TMC} < 110$	
G	$\eta_{TMC} < 85$	

$P_{on, Max}$ (W)

$P_{onmax} = C \times (L + \Phi_{use}/(F \times \eta)) \times R;$	C	1.23
	L	1.5
	Useful luminous flux (Φ_{use})	525
	F	0.85
	R	1
	η	120

References to the harmonised standards applied or other standards used

EN 60968 EN 62031 EN 62471
EN 55015 EN 61000-3-2 EN 61000-3-3 EN 61547
EN 62717 EN 62612 EN 13032-4

Testing conditions if not described sufficiently in the standard

Ta: 25°C
Test Voltage: 230V 50Hz

Control settings, and instructions on how they can be implemented

Refer to electrical ratings and ensure the light source is not dimmed. Item doesn't have any specific settings.

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

Not applicable

Specific precautions that shall be taken when the model is assembled, installed, maintained or tested

- 1.This light is only suitable for use in indoor, dry and enclosed areas. This product is only intended for private household use
- 2.Children may not play with the product. Children may not carry out cleaning and maintenance activities without supervision. This product is not a toy.
- 3.Before using the light, make sure that the supply voltage matches the required operating voltage for the light (220–240 V AC, 50 Hz) in a GU10 socket.
- 4.To avoid burns, make sure that the light is switched off and has cooled down before you touch it. Lamps can get very hot.
- 5.Do not cover the lamp with any other objects. Overheating can cause fire.
- 6.Do not leave the light unattended while it is on.
- 7.Install by gently pushing the product into a GU10 socket, making sure that pins are aligned with the socket. Then gently turn clockwise until you feel resistance.
- 8.Remove by gently pushing the product into the socket and gently turning anti-clockwise until you feel resistance. Then gently pull the product out of the socket.

Disposal recommendations at the end of the light source's life time (Directive 2012/19/EU)

Translations and national adaptations are included in the user manual of the item, supplied with the light source or its containing product.

The Waste Electrical and Electronic Equipment (WEEE) Directive aims to minimise the impact of electrical and electronic goods on the environment, by increasing re-use and recycling and by reducing the amount of WEEE going to landfill. The symbol on this product or its packaging signifies that this product must be disposed separately from ordinary household wastes at its end of life. Be aware that this is your responsibility to dispose of electronic equipment at recycling centers in order to conserve natural resources. Each country should have its collection centers for electrical and electronic equipment recycling.

For information about your recycling drop off area, please contact your related electrical and electronic equipment waste management authority, your local city office, or your household waste disposal service.

This light source is dimmable:

No

Light source is designed to be used in the following products. Use in other products may cause damage or risk to users.

46680.7.06